

Quick Reference Guide VEGA DTM Installation Guide



Document ID: 58263





Revision History

Version of manual	Description	Date	
1.0	Initial release	180713	

This document contains proprietary information of VEGA Americas, Inc. It shall not be reproduced in whole, or in part, in any form, without the expressed written permission of VEGA Americas, Inc.

The material in this document is provided for informational purposes only and is subject to change without notice.

ISO 9001:2015 approval by Eagle Registrations Inc. to these Quality Management System Standards: ASQ/ANSI/ISO 9001:2015, Approval Certificate No. 5504.

NOTES

Table of Contents

Revision History	3
Table of Contents	5
Overview	6
Uninstall the Current DTM	8
Download New DTM	9
Install New DTM Collection	11
Installation Wizard	11
Installation Completion	12

NOTES

Overview

This quick reference guide is intended as a guide for field support personnel when explaining the VEGA DTM installation procedure. These installation instructions are available from the VEGA website at https://www.vega.com/en/home_us/Services/Field-Service-Repair

Uninstall the Current DTM

Before you install the new DTM, you must uninstall any previous version of the DTM that are installed on your computer. Complete the following steps to remove old versions of the DTM.

- 1. Click Start > All Programs > VEGA > VEGA-DTM Tools > Uninstall VEGA-DTM.
- 2. Follow the steps provided in the DTM wizard to finish the uninstall.



Figure 1: Uninstall DTM Method 1

Depending on the computer you are using, you may not find the **Uninstall VEGA-DTM** feature in the **Start** menu. If that is the case, follow these steps:

- 1. Go to the Control Panel.
- 2. Click Programs and Features.
- 3. Click the old VEGA-DTM version.
- 4. Click Uninstall.

<	Control P	and 7 Ai Control Panel items 7 Programs and reatures		V 0 56	ICT PT 7	<u></u>
Control Panel Ho	me	Urinstall or change a program				
View installed upo	dates	To uninstall a program, select it from the list and then	click Uninstall, Change, or Repair.			
Turn Windows features on or off Install a program from the network	atures on or	Organite 🔻	Contract of the Lorent Processing Acres		BI • (?
	from the	Name Unitronics Remote Access Unitronics VisiLogic C	Publisher	Installed On 6/15/2018 6/28/2018	Size	
		🗌 😴 VEGA-DTM 1.81.1	VEGA Grieshaber KG	6/26/2018	1.07	0
		VEGAOutlookAddIn2007 Vsual Studio 2010 Prerequisites - English Windows 10 Update and Privacy Settings Windows 10 Update Assistant Windows Driver Package - SEGGER (USBBulk) USB	VEGAOutlookAddIn2007 Microsoft Corporation Microsoft Corporation Microsoft Corporation SEGGER	6/1/2018 1/17/2017 6/8/2017 8/25/2017 10/9/2017	47.1 2.10 5.00	
		<				•
		Currently installed programs Total size:	7.78 GB			

Figure 2: Uninstall DTM Method 2

Download New DTM

After successfully removing the old version of the DTM, download the newest version of the DTM using these steps.

- 1. In your browser, type <u>www.vega.com</u>.
- 2. Click Downloads.
- 3. Click Software.
- 4. Click DTM Collection + PACTware.

VEGA		United States	🔀 Erglish	m 'C bar	Contact	P myVEGA
Products Applications Downloads Girl > Downloads	Services: Company				Search	Q
Downloads						
Search in downloads C	Adjustment software: DTM Collection - PACTware (7)					+
Product related downloads	Device software (Firmware) (58)					+
selected product	Device hardware (version history) (14)					+
- Product catalog	Device driver AMS Device Library (DD) (4)					+
- Product family	C Device driver · Foundation Fieldbus (FF) (10)					+
General Downloads Company and industry information, produc	Device driver · PDM Device Library (EDD) (39)					+
independent software and further documents.	Device driver Profibus (DP/PA) (19)					+
Brochures	Fieldbus (4)					+
Software						
Forms and Certificales	Adjustment software: VVO (4)					+
C Reset						

Figure 3: Download DTM

5. Select the latest DTM version listed.

Adjustment software: DTM Collection + PACTware (7)	-
Software - Adjustment software: DTM Collection + PACTware VEGA DTM Collection Collection of all VEGA device DTMs as well as communication DT FDT framework program such as PACTware is required). File size DTM Collection Used only for updating exis	181.1 く Software Ms for parameterization (an is 580 MB. 第 く Supported instruments ting DTM collections (does not include PACTware) 第 く Version history
Software - Adjustment software: DTM Collection + PACTware PACTware 5.0 Framework program of the PACTware Consortium e. V. (can be u conjunction with DTMs). File size is 35 MB. Pactware	seed as operating software in Image: Seed as operating software only - used primarily for updating from PACTware versions (Does not include the VEGA DTM collection)
Software - Adjustment software: DTM Collection + PACTware VEGA-DTM VEGADIF 55 HART Version 1.4.129 VEGA DTM	1.4.129 Software
Software - Adjustment software: DTM Collection + PACTware Generic HART DTM Version 4.0.3 Standard DTM foradjustment of individual HART sensors via Un (manufacturer: ICS) third party vendor	4.0.3 Software
Software - Adjustment software: DTM Collection + PACTware HART Driver Version 1.0.52 Communication DTM for use of HART modems (manufacturer: C third party vendor	1.0.52 Software
Software - Adjustment software: DTM Collection + PACTware PROFIdtm Version 2.10 Communication DTM for communication via Profibus DP with So (manufacturer: Softing) third party vendor	2.1 Software
Software - Adjustment software: DTM Collection + PACTware PACTware and VEGA DTM Collection File size 1.3 GB Complete package	This software package contains the latest vesions of PACTware and the VEGA DTM collection - used primarily for fresh installs when all components are needed. (Download this package if unsure of current software state)

Figure 4: Latest DTM Version

Install New DTM Collection

Once the download of the DTM collection is finished, you can begin the installation. Follow the steps below to start the installation of the new DTM.



The DTM may have downloaded in the bottom left corner of the web page or in the download folder on your computer.

- 1. After locating the downloaded files, click the executable.
- 2. The **User Account Control** dialog box appears asking "Do you want to allow this app to make changes to your device?".
- 3. Click Yes.
- 4. Wait while the file self-extracts.
- 5. From the **InstallShield Wizard** dialog box, click the **Language** drop down list and select the language you wish to use.
- 6. Click OK.

Installation Wizard

Once the DTM is extracted and the appropriate language is chosen, the DTM installation wizard opens. Complete the following steps to finish installing the DTM.

1. Click Next.



Figure 5: Install Wizard Next

- 2. Read through or print the license agreement.
- 3. Click Yes.



Figure 6: DTM License Agreement

4. Follow the remaining installation wizard instructions to complete the rest of the DTM installation.

Installation Completion

After the installation wizard is complete, the VEGA DTM Selector dialog box appears and asks which DTMs wish to select.



Figure 7: VEGA DTM Selector

I. NOTE

VEGA recommends leaving all the check boxes selected.

1. Click OK.

After the DTM collection installation has completed, the optional registration dialog box opens. You can receive updated software and news by registering.

/EGA-DTM Version X.XX.X - Full	version
	InstallShield Wizard Complete The InstallShield Wizard has successfully installed VEGA-DTM X.XX.X. Clck Finish to exit the wizard.
plics	Information about DTM updates The VEGA DTM-Collection is constantly improved. You can find all relevant software information at our home page including software history, updates, patches and so on. Alternatively we can inform you automatically about updates of the DTM-Collection via email. For this service please put your contact details on to the mailing list Register now
Instalisticid	< <u>B</u> ack Finish Cancel

Figure 8: Optional DTM Registration



An internet connection is required for DTM registration.

- 2. If you choose not to register, uncheck the Register now box.
- 3. Click Finish.

NOTES



VEGA Americas, Inc. 4170 Rosslyn Drive Cincinnati, Ohio 45209 USA Phone: 1.513.272.0131 Fax: 1.513.272.0133 E-mail: americas@vega.com www.vega.com

> All statements concerning scope of delivery, application, practical use, and operating conditions of the sensors and processing systems correspond to the information available at the time of printing.

©2018 VEGA Americas, Inc. Cincinnati, Ohio, USA